### **Products**

## - Security & Sensors





## **Description**

The PIR313 Multi-sensor is used to measure the ambient temperature, humidity, motion and illuminance. It support Tuya scene and receive notifications from mobile app.

#### **Main Features**

- ZigBee 3.0
- PIR motion detection
- Temperature and humidity measuring
- Illuminance measurement
- · Long battery life
- Low battery alerts
- Anti-tamper
- Sleek design
- Support OTA

# **Main Specifications**

Connectivity	
ZigBee	• 2.4GHz IEEE 802.15.4
ZigBee Profile	• ZigBee 3.0
RF Characteristics	<ul> <li>Operating frequency: 2.4GHz</li> <li>Internal PCB Antenna</li> <li>Range outdoor: 100m (Open area)</li> <li>Anti-RF Interference: 10MHz - 1GHz 20V/m</li> </ul>
Physical Specifications	
Battery	• DC 3V (Two AAA batteries)
Rated Current	<ul><li>Standby Current: ≤40uA</li><li>Alarm Current: ≤110mA</li></ul>
Illuminance (Photocell)	<ul><li>Range:0~128klx</li><li>Resolution:0.1lx</li></ul>
Temperature	<ul><li>Range:-10~85°</li><li>Accuracy: ± 0.4°</li></ul>
Humidity	<ul><li>Range:0~80%RH</li><li>Accuracy: ± 4% RH</li></ul>
Reporting Cycle	Temperature/Humidity: 1min
Detecting	<ul> <li>Distance: 6m</li> <li>Angle: 120°</li> </ul>
Operating environment	<ul> <li>Temperature: -10 °C~+50 °C</li> <li>Humidity: ≤ 90% non-condensing</li> </ul>
Dimension	• 83(L) x 83(W) x 28(H) mm
Weight	• 65g
Mounting Type	Tabletop stand or Wall mount